

ENSEMBLE

D E S I G N S

rlz 11-21-97

Installing DS-1 Smart Store SIMM's

If you are replacing a Smart Store SIMM in sockets J21 - J26 of the 50001201 DS-1 Motherboard, remove the original part by pressing outward on the retaining clips at the bottom of the socket. Gently push rearward at the top of the SIMM while releasing the retaining clips. Do not use excessive pressure or the Smart Store could be damaged. When the retaining clips are released the SIMM will tilt backward about 30 degrees. Lift the Smart Store SIMM upward and out of the socket.

The proper orientation for the SIMM is with the Smart Store legend forward so that it can be read from the front of the DS-1. To install a new Smart Store SIMM slide it down into the socket with the SIMM tilted rearward. Press down firmly and move the top of the SIMM forward until it is vertical and the retaining clips are engaged. Note that it is level and properly seated in the socket.

In case of questions or problems please call Ensemble Designs at 530-478-1830.